


# k

## kiva xl



**fully  
prefabricated**



**tough  
ALU door**



**massive  
interior**



**single  
glazing**



**dynamic  
facade**

### Standard configuration:

DIMENSIONS	322 x 208 x 230 cm
WEIGHT	1400 kg
WINDOWS / GLAZING	Front side single glazing 8mm / transparent glass
DOOR	Aluminium frame, non-locking, single glazed
FLOORING	HPL
INTERIOR WALLS	Rustic tyrol wood cladding, heat treated and brushed
BENCHES	Thermo aspen
BACKREST	Thermo aspen
CONTROL UNIT	Premium touch control panel
COLOR LIGHT THERAPY	LED RGB under the bench and behind the backrest incl. remote control
HEATER	NN Standard heater gkW
FACADES	Glass, tyrol lamellas natural, sheet metal on the back side
RAINWATER DRAINAGE	Along the rear-side drip plate

### Available options:

GLAZING	Parsol dark grey, mirror
DOOR	Door lock, antipanic - EN179
FACADES	Tyrol lamellas black painted
HEATERS	Fin and Bio heaters from other manufacturers by request
ILLUMINATION	Digital addressable LED interior illumination, outdoor ambient illumination below sauna, vertical LED stripes integrated in facade
IR HEATERS	Up to 3 pcs full spectrum heaters



## Conditions to be provided by the customer:

**POWER CABLE:** 400V / 5 x 2.5 mm<sup>2</sup> wire gauge, 3 x 16 Amp C-type fuse, 2 meter length, equipped with 400 volt 16A-6p-6h IP44 female connector. Your sauna will be supplied with the corresponding compatible connector, facilitating a hassle-free and secure electrical connection.

**FOUNDATION:** Flat and solid; a reinforced concrete slab, matching the dimensions of the sauna, with a thickness of 15 cm, the sauna is set on adjustable feet for leveling and alignment.

**INSTALLATION:** Accessibility to the installation site for crane delivery must be checked and ensured. **IMPORTANT:** It is the customer's responsibility to arrange for the crane or other delivery means and to clarify all requirements for installation in advance.

**DELIVERY & ASSEMBLY:** The sauna is prefabricated in the factory and is delivered directly to the construction site by prior arrangement. Generally, the customer is responsible for organizing all installation measures unless otherwise agreed. Final assembly, including electrical connection for testing, commissioning, functional testing, training, and handover will be carried out by the seller's or manufacturer's assembly team.

